Crestron[®] Control App for Zoom Rooms[®] Software

Control App



The Crestron® Control App for Zoom Rooms® Software allows custom user interfaces to be added to the Zoom Rooms controller application using <u>Crestron HTML5 User Interface</u> and <u>Crestron Construct™</u> technologies. The app enables custom control logic and third-party device support for the Zoom Rooms controller application, providing a tailored Zoom Rooms user experience that fits the specific needs of an enterprise.

The Crestron Control App for Zoom Rooms is compatible with supported <u>Crestron Flex for Zoom Rooms solutions</u> when paired with a compatible 3-Series®, <u>4-Series®</u> or <u>Crestron</u> <u>Virtual Control (VC-4)</u> control system^{1,2,4}. The associated program is loaded to a program slot (3-Series and 4-Series control systems) or room (Crestron Virtual Control), allowing multiple Zoom Rooms systems to be hosted on a single control system³. The app is also compatible with <u>.AV Framework™</u> software.

The following Zoom Rooms controllers have been verified for use with the app by Crestron:

- Apple[®] iPad[®] device⁴
- Crestron Mercury[®] mini conference systems
- Crestron® TS-770 and TS-1070 series touch screens
- Crestron TSW-770 and TSW-1070 series touch screens
- Crestron TST-1080 touch screen
- Logitech® Tap IP touch screen
- Neat Pad[®] touch screen
- Poly® TC8 touch screen
- Poly TC10 touch screen

The following Zoom Rooms controllers have been verified for use when operating in a Windows® OS attached configuration:

- Crestron Mercury[®] conference systems
- Crestron Mercury X conference systems
- Crestron TSW-1060 touch screen
- Logitech® Tap touch screen

NOTE: Additional Zooms Rooms controllers are supported using the custom resolution feature in the Crestron Construct IDE.

The app is available in the <u>Zoom® App Marketplace</u> and must be deployed via the Zoom Portal. For more information, refer to the <u>Crestron Control App for Zoom Rooms Software</u> <u>Product Manual and Crestron Control for Zoom Rooms</u> <u>Software Online Help</u>.

Specifications

Minimum Requirements

Crestron [®] Control System	3-Series® control system, firmware version 1.8001.0251 or greater ² ; 4-Series® control system, firmware version 2.8004.00042 or greater ⁴ ; Crestron Virtual Control (VC- 4), software version 4.0004.00069 or greater
Zoom Rooms® System	Software version 5.16.5 or higher; TS/TSW-1070 series, TST-1080, or Crestron Flex Mini Tabletop conference device; Compatible with select third-party Zoom Rooms controllers
Crestron HTML5 User Interface	SDK version 2.7 or higher
Embedded ZRC Web Browser	Chromium version 98 or higher
.AV Framework™ Software	Software version 7.00 or higher

Model

Crestron® Control App for Zoom Rooms® Software Control App



Crestron[®] Control App for Zoom Rooms[®] Software

Control App

Notes:

- Refer to Specifications for supported Crestron[®] control systems and Zoom Rooms[®] system components. The control system must be connected to the internet to deploy and run the app.
- 2. The DMPS3-4K-50, DMPS3-4K-150-C, MC3, and TPCS-4SM control systems are not compatible with the Crestron Control App for Zoom Rooms.
- Certain 4-Series[®] control systems ship with one program slot enabled by default. Up to 10 simultaneous programs can be run on these control systems by enabling Modular Programming Architecture (MPA), which requires the purchase of one <u>SW-RMC3-10PROG</u> license. Only one Crestron Control App for Zoom Rooms program can be run on a 3-Series[®] control system regardless of its MPA support.
- 4. Apple® <code>iPad®</code> devices running as Zoom Rooms controllers are supported on 4-Series control systems only.

The original language version of this document is U.S. English. All other languages are a translation of the original document.

The specific patents that cover Crestron products are listed online at www.crestron.com/legal/patents.

Certain Crestron products contain open source software. For specific information, please visit www.crestron.com/opensource.

Crestron, the Crestron logo, .AV Framework, 3-Series, 4-Series, Crestron Construct, and Crestron Mercury are either trademarks or registered trademarks of Crestron Electronics, Inc. in the United States and/or other countries. Apple and iPad are either trademarks or registered trademarks of Apple, Inc. in the United States and/or other countries. Poly is either a trademark or a registered trademark of HP Inc. in the United States and/or other countries. Logitech is either a trademark or a registered trademark of Logitech, Inc. in the United States and/or other countries. Windows is either a trademark or a registered trademark of Microsoft Corporation in the United States and/or other countries. Neat Pad is either a trademark or a registered trademark of Neatframe Ltd. in the United States and/or other countries. Zoom and Zoom Rooms are either trademarks or registered trademarks of Zoom Video Communications, Inc. in the United States and/or other countries. Other trademarks, registered trademarks, and trade names may be used in this document to refer to either the entities claiming the marks and names or their products. Crestron disclaims any proprietary interest in the marks and names of others. Crestron is not responsible for errors in typography or photography.

Specifications are subject to change without notice.

©2024 Crestron Electronics, Inc.

Rev 08/14/24

